

Coax Loss Chart dB per 100 Feet

	RG-316	RG-58	RG-8X	LMR-240	RG-213	9913	LMR-400	Bury-Flex
3.5 MHz	1.5	.8	.65	.45	.3	.23	.2	.26
7 MHz	2.1	1.2	.85	.64	.5	.32	.3	.37
14 MHz	3.0	1.7	1.21	.91	.7	.46	.5	.53
28 MHz	4.2	2.4	1.74	1.29	1.00	.65	.7	.75
50 MHz	5.6	3.2	2.36	1.73	1.40	.88	.9	1.00
144 MHz	9.6	5.5	4.20	2.95	2.40	1.54	1.44	1.73
440 MHz	17	9.9	7.92	5.23	4.40	2.818	2.7	3.08
2400	41.4	24.8	22.80	12.65	12	7.48	6.6	7.63